

# GBG - 2 SERIES

## Gasoline Generators



### Features and Benefits

- Half century experience in generator manufacturing
- Gasoline engines with advanced technology and quality
- Alternators with advanced technology and quality
- Easy to Carry
- High quality and reliable technology
- Compact Design and Silent
- Suitable for heavy-duty
- Durable
- Wide range of affordable spare parts
- Low noise level
- Low exhaust emission
- Low operating cost
- Low fuel consumption
- Low oil consumption
- Lightweight
- Big Size Fuel Tank
- First class product support
- Global technical service and maintenance support

#### CAUTION: Important Notes;

**Note 1:** Never use the generator indoors

**Note 2:** Wait at least 20 minutes for generator to cool off before refuel

**Note 3:** Do not refuel while the generator is still running

**Note 4:** Do not use the generator for longer than the continuous operating hours written on the catalog

#### Factory Address

ASO II. Industrial Zone  
2010 Street No: 18  
06909 Temelli-Sincan/Ankara, Turkey  
Tel/ Fax: +90(312) 641 32 22 - 641 32 23  
genpower@genpower.com.tr  
www.genpower.com.tr



# GENPOWER

GENERATOR

# GBG 10000TE

## PRODUCT DATASHEET

### GENERATOR

Type	
Max. Output Power	kVA
Rated Output Power	kVA
Power Factor	Cos Q
Frequency	Hz
Voltage	V
Current	A
Noice Level (from 7 meter @ 1/4 Load)	dB(A)

	Open Type Standard Portable Generators
	10
	8,8
	0,8
	50
	231/400
	3x12,7
	≤74

### GASOLINE ENGINE

Type	
Model	GBE
Series	
Displacement	cc
Bore x Stroke	mm
Compression Ratio	
Ignition	
Fuel Tank Capacity	Lt
Run Time @ %50 Load	Hour
Fuel Consumption	Lt/h
Oil Capacity	Lt
Engine Start System	
Speed	rpm

	OHV, Single Cylinder, Forced Air Cooled, Four Stroke
	460
	KP
	459
	92 x 69
	8.5:1
	TCl - Transistor Electronic Ignition
	30
	6
	0,374 gr/kWh - 2,63 Lt/h with Full Load
	1,1
	Electric Start/Recoil
	3000

### ALTERNATOR

Model	
Type	
Phase	
Voltage Regulation	
Protection Class	
Insulation Class	
Wire	100%
THD (Total Harmonic Distorsion)	%

	150L
	Self Excited, Synchron Alternator
	Three Phase
	AVR
	IP23
	H/F
	Copper
	≤10-15

### OTHER DATA

Over Load Protection	
Low Oil Alert	
Reset Socket	
European Socket	
Analog Voltmeter	
3-in-1 director light(oil, output, overload alert)	
Engine Switch	
3 in 1 Digital Display	
DC Socket (12V/8,3A)	
DC Protector	
USB Socket	
Parallel Socket	
Grounding Terminal	
Wheel and Handle	
Certification	

	√
	√
	√
	√
	√
	-
	√
	-
	√
	√
	-
	-
	√
	√
	CE/EUS/EPA

### DIMENSIONS

Package	
Carton Size	mm
Net Weight/Gross Weight	Kg
Container Loading Qty's 20GP/40GP/40HQ	Pcs

	Carton
	680x510x540
	81/83
	120/256/256

# GENPOWER

GENERATOR